

## DIMM - DUAL INPUT MONITOR MODULE



### STANDARD FEATURES

- Fast, reliable contact monitoring utilizing the Hochiki **DCP** (Digital Communications Protocol)
- 127 devices can be used per **DCP** loop
- Bi-colored indicating LED provides module status
- Dual input contact monitor
- Can be programmed to monitor Normally Open (NO) or Normally Closed (NC) contacts
- Operates on Class A or Class B SLC loop
- Accepts up to 14 AWG wire
- Mounts to 4" square gang box

### PRODUCT LISTINGS

Underwriters Laboratories: S5694  
CSFM #: 7300-0410:150

### SPECIFICATIONS

Operating Voltage:	17~41 VDC
Average Current Consumption:	600 $\mu$ A(Typical)
Alarm Current:	30mA
Dimensions:	4.2"W x 4.7"H x 1.4"D
Ambient Temperature:	32°F (0°C) ~ 120°F (49°C)
Max. Humidity:	90% RH, non-condensing
Mounting:	4" square electrical box

### DESCRIPTION

The Hochiki Dual Monitor Module (DIMM) is designed for use on the FireNET analog addressable system. It provides two independent contact monitoring circuits while only utilizing one address on the SLC loop. Up to 127 devices can be placed on a single SLC loop. The device address is uniquely stored on an onboard EEPROM. The module can be programmed to monitor normally open (NO) or normally closed (NC) contact fire alarm and supervisory devices. The interrupt driven Digital Communication Protocol (DCP) combines maximum communication reliability and fast response to emergency conditions. The module has a single bi-colored LED to indicate device status. It fits into a standard 4" square or double gang electrical back box.

# ENGINEERING SPECIFICATIONS

The contractor shall furnish and install where indicated on the plans, addressable contact monitoring modules Hochiki DIMM. The modules shall be UL listed and compatible with the Hochiki FireNET fire alarm control panel. The device address shall be electrically programmable and stored in EEPROM. A bi-colored LED shall indicate device status.



Back Side of a DIMM

# WIRING DIAGRAM

